
H08

Hands-On: IMS ETO Support for z/OS

Scott Salava



St. Louis, MO

September 30 - October 3, 2002

Note:

References in this document to IBM products (including programs or services), do not imply that IBM intends to make these available in all countries in which IBM operates. Any reference to an IBM product in this document is not intended to state or imply that only IBM's product may be used. Any functionally equivalent product may be used instead, although the services described as part of this offering may vary based on non-IBM Vendor agreements. Evaluation is the responsibility of the customer.

IBM may have patents or pending patent applications covering subject matter in this document. The furnishing of this document does not give you any license to these patents. You can send license inquiries, in writing to the IBM Director of Commercial Relations, IBM Corporation, Purchase, NY 10577.

TM Copyright: International Business Machines, Inc. 2002

Workshop Overview

The goal of this workshop is to learn to use IMS ETO Support and to become familiar with some of its options.

Exercise 2. Using IMS ETO Support

What This Exercise is About

In this exercise students will logon to the IMS system and work with IMS ETO Support. After logging in, activities include starting IZTRAN, viewing ETO options, changing LTERMS and dynamically refreshing ETO configurations.

Exercise Steps

- ___ 1. Logon to IMSA.
- ___ 2. Sign on to IMS. Your USERID ==> TEAMxx, PASSWORD ==> TEAMxx.
- ___ 3. Execute IZTRAN. Type IZTRAN and press Enter.

```
IZTRAN                                IMS ETO-SUPPORT                                IMSID:  IMS7
COMMAND ===>                          VERSION - 02.02.00                                RELEASE: 7.1.0
                                      PRIMARY MENU

CUSTOMIZE OPTIONS                      VIEW OPTIONS
A - GLOBAL OPTIONS                    1 - GLOBAL OPTIONS
B - DEVICE TYPE OPTIONS                2 - DEVICE TYPE OPTIONS
C - LU NAME SPECIFIC OPTIONS           3 - LU NAME SPECIFIC OPTIONS
D - USER SPECIFIC OPTIONS              4 - USER SPECIFIC OPTIONS
E - COMMAND SECURITY OPTIONS            5 - COMMAND SECURITY OPTIONS
F - COMMAND/KEYWORD SECURITY            6 - COMMAND/KEYWORD SECURITY
G - SECURITY GROUP COMMANDS             7 - SECURITY GROUP COMMANDS
H - PRINTER LTERM DEFINITIONS           8 - PRINTER LTERM DEFINITIONS
I - DFS3649A ERROR MESSAGES             9 - DFS3649A ERROR MESSAGES

TEST FACILITIES                        EXIT RELOAD
T - TRANSLATION TABLE LOOKUP          R - RELOAD IMS EXITS

TABLE REFRESH OPTIONS
Y - CUSTOMIZE REFRESH ROUTING DATA
Z - PERFORM TABLE REFRESH
```

- ___ 4. Perform Translation Table Lookup
 - a. Type T in the Command line and press Enter.

b. Type 2 for selection 2 - SLU2 / 3270 and press Enter.

```

IZTRAN                IMS ETO-SUPPORT                IMSID:  IMS7
COMMAND ===>          VERSION - 02.02.00            RELEASE: 7.1.0
                        SLU2 TRANSLATION LOOKUP

LUNAME  ===>
USERID  ===>
SEARCH  ===>          1 - SEARCH DATA BASE
                        2 - SEARCH E/CSA TABLE ----- ENTRY TYPE -----
                                                =DEVICE= =GLOBAL=

LOGON PROCESS  ===>
DFS3649 OPTION ===>
DFS3650 OPTION ===>
LTERM/USER NAMES ===>
ASOT           ===>
ALOT           ===>
RESPONSE       ===>
MSGDEL         ===>
LOGON DESCRIPTOR ===>
DEVICE MODEL   ===>
SECURITY GROUP ===>
USER/LTERM NAME ===>

```

c. Type your user ID in the USERID line, type 2 in the SEARCH line and press Enter.

```

IZTRAN                IMS ETO-SUPPORT                IMSID:  IMS7
COMMAND ===>          VERSION - 02.02.00            RELEASE: 7.1.0
                        SLU2 TRANSLATION LOOKUP

LUNAME  ===>
USERID  ===> IBMUSER
SEARCH  ===> 1        1 - SEARCH DATA BASE
                        2 - SEARCH E/CSA TABLE ----- ENTRY TYPE -----
                                                =LUNAME= =USERID= =DEVICE= =GLOBAL=

LOGON PROCESS  ===> ETO-SUPPORT                      GLOBAL
DFS3649 OPTION ===> IMS DEFAULT                      GLOBAL
DFS3650 OPTION ===> IMS DEFAULT                      GLOBAL
LTERM/USER NAMES ===> IMS DEFAULT                    GLOBAL
ASOT           ===> 1440                             GLOBAL
ALOT           ===> 0090                             GLOBAL
RESPONSE       ===>
MSGDEL         ===>
LOGON DESCRIPTOR ===>
DEVICE MODEL   ===>
SECURITY GROUP ===>
USER/LTERM NAME ===>

```

d. Review your default IMS options and the tables in which they currently reside.

e. After you finish your review, press PF4 to return to the IMS ETO Support Primary Menu.

5. Create a USERID table entry.

a. Type D in the Command line and press Enter.

```

IZTRAN                                IMS ETO-SUPPORT                                IMSID:  IMS7
COMMAND ===>                          VERSION - 02.02.00                                RELEASE: 7.1.0
START  ===>                             USERID MEMBER LIST

SEL  MEMBER          SEL  MEMBER          SEL  MEMBER          SEL  MEMBER
---  - - - - -      ---  - - - - -      ---  - - - - -      ---  - - - - -

ROW COMMANDS: "S" OR "E" - TO EDIT ENTRY, "D" - TO DELETE ENTRY
COMMAND LINE: "A" OR "ADD" - TO ADD AN ENTRY, "F" - FORWARD, "B" - BACKWARD

```

- b. Type A in the command and press Enter.
 - c. Type your user ID in the USERID line. Tab to LTERM/USER NAMING OPTIONS. Type 3 to select USERID FROM TABLE option. Tab to USER/LTERM in the lower right. Type a new LTERM name.
- You can add up to 8 LTERM names at this point.
- d. Press Enter.

```

IZTRAN                                IMS ETO-SUPPORT                                IMSID:  IMS7
COMMAND ===>                          VERSION - 02.02.00                                RELEASE: 7.1.0
USERID ===> IBMUSER                    USERID OPTIONS

DFS3650
 1 - IMS DEFAULT
 2 - DFS058 MESSAGE
 3 - BLANK SCREEN
 4 - USER DFSGMSG1
 5 - USER MOD

LTERM/USER NAMING OPTIONS:
3  1 - IMS DEFAULT          IDLE NODE TIMEOUT: (BLANKS, 0000, 0010-1440)
   2 - NODE=USER=LTERM      ASOT
   3 - USERID FROM TABLE
   4 - SUFFIXED USERID      SECURITY GROUP
   5 - USER DFSSGNX1

RESPONSE OPTIONS:  MSGDEL OPTIONS:  ===== USER/LTERMS =====
 1 - NORESP        1 - SYSINFO      SALAVA
 2 - FORCRESP      2 - NOTERM
 3 - TRANRESP      3 - NONIOPCB

IZT5771I - RECORD ADDED TO DBIZT1

```

- e. Review the Record Added message on the USERID OPTIONS screen. Your LTERM has been successfully loaded into the database.
- f. Press PF4 to return to the IMS ETO Support Primary Menu.

___ 6. Perform Table Refresh to load the updated table into E/CSA

- a. Type Z on the command line to select the Perform Table Refresh option and press Enter.

```
IZTRAN                      IMS ETO-SUPPORT                      IMSID:  IMS7
COMMAND ===>                VERSION - 02.02.00                      RELEASE: 7.1.0
                              E/CSA TABLE REFRESH

REFRESH SELECTIONS
A - GLOBAL OPTIONS
B - DEVICE TYPE OPTIONS
C - LU NAME SPECIFIC OPTIONS
D - USER SPECIFIC OPTIONS
E - COMMAND SECURITY OPTIONS
F - COMMAND/KEYWORD SECURITY
G - SECURITY GROUP COMMANDS
H - PRINTER LTERM DEFINITIONS
I - DFS3649A ERROR MESSAGES
```

- b. Type D on the command line to select User Specific Options and press Enter.

```
IZTRAN                      IMS ETO-SUPPORT                      IMSID:  IMS7
COMMAND ===>                VERSION - 02.02.00                      RELEASE: 7.1.0
                              E/CSA TABLE REFRESH

SYMDEST      SYMDEST      SYMDEST      SYMDEST      SYMDEST      SYMDEST
-----      -
SYS1

IZT2013I - E/CSA REFRESH COMPLETED
```

- c. Review Refresh Completed message on the E/CSA Table Refresh screen. E/CSA is now updated.
- d. Press PF4 to return to the IMS ETO Support Primary Menu.

___ 7. Review the Translation Table.

- a. Type T on the command line and press Enter. Type 2 on the command line and press Enter. Type your USERID and use Search option 2. Press Enter.

```

IZTRAN                IMS ETO-SUPPORT                IMSID:  IMS7
COMMAND ==>          VERSION - 02.02.00                RELEASE: 7.1.0
                                SLU2 TRANSLATION LOOKUP

LUNAME ==>
USERID ==> IBMUSER
SEARCH ==> 2      1 - SEARCH DATA BASE
                                2 - SEARCH E/CSA TABLE  ----- ENTRY TYPE -----
                                                                =LUNAME= =USERID= =DEVICE= =GLOBAL=

LOGON PROCESS ==> ETO-SUPPORT                                GLOBAL
DFS3649 OPTION ==> IMS DEFAULT                                GLOBAL
DFS3650 OPTION ==> IMS DEFAULT                                GLOBAL
LTERM/USER NAMES ==> USERID FROM TABLE                    IBMUSER
ASOT ==> 1440                                                GLOBAL
ALOT ==> 0090                                                GLOBAL

RESPONSE ==>
MSGDEL ==>
LOGON DESCRIPTOR ==>
DEVICE MODEL ==>
SECURITY GROUP ==>
USER/LTERM NAME ==> SALAVA                                IBMUSER

```

- b. Review the updated information on the SLU2 Translation Lookup screen.
- c. Press PF4 to return to the IMS ETO Support Primary Menu.

___ 8. Establish your new LTERM for your user ID.

- a. Press PF3 to exit IMS ETO Support.
- b. Type /sig off and press Enter.

```

/sig off

IZT5000I - IZTRAN PROCESSING COMPLETE

```

- c. Sign on to IMS again. Your USERID ==> TEAMxx, PASSWORD ==> TEAMxx.

d. After you have successfully signed on, type /dis asmt user <TEAMxx>.

```
/dis asmt user ibmuser  
  
DFS3650I SESSION STATUS FOR IMS IMS7  
  
DATE: 08/22/02      TIME: 02:29:40  
NODE NAME:          LCL701  
USER:               SALAVA  
PRESET DESTINATION:  
  
CURRENT SESSION STATUS:  
  
      OUTPUT SECURITY AVAILABLE
```

e. Review your LTERM as you entered it in IMS ETO Support.

```
      USER      USERID  ID      NODE  
SALAVA  IBMUSER          LCL701  I/O- SALAVA  
*02234/023034*
```