


IBM

Version 1.4.3



Upgrade Guide

Note: Before using this information and the product it supports, read the information in “Notices” on page 33.

This edition applies to version 1, release 4, modification 3 of IBM Tivoli Netcool Service Quality Manager GSM service solution and to all subsequent releases and modifications until otherwise indicated in new editions.

© Copyright International Business Machines Corporation 2008, 2009, 2010. All rights reserved.

US Government Users Restricted Rights - Use, duplication or disclosure restricted by GSA ADP Schedule Contract with IBM Corp

Table of Contents

1	About this Documentation	5
1.1	Audience.....	5
1.2	Required Skills and Knowledge	5
1.3	Document Conventions	6
1.4	User Publications	7
2	Software Requirements	10
3	Hardware Specification	11
4	Upgrade Procedure	12
4.1	Stopping the GSM Loaders	12
4.2	Removing GSM 1.4.2 Loader deployment files	13
4.3	Backing up the GSM Loader Configurations	13
4.4	Installing GSM GOM Version 1.4.3.....	14
4.5	Installing GSM RAN PM Version 1.4.3.....	15
4.6	Installing GSM MSC PM Version 1.4.3	15
4.7	Installing GSM E2E AT Version 1.4.3	16
4.8	Installing GSM SS7 Version 1.4.3.....	17
4.9	Upgrading the GSM Provisioning to Version 1.4.3	17
4.10	Deploying the Version 1.4.3 Loaders	18
4.11	Restoring the GSM Loader Configurations.....	19
4.12	Upgrading the GSM RAN PM Schema	19
4.13	Upgrading the GSM SS7 Schema	20
4.14	Deploying GSM version 1.4.3 BO™ Universes	20
4.14.1	Prerequisite.....	20
4.14.2	Extracting BusinessObjects deliverables	20
4.14.3	Associating LOV files with universe	21
4.14.4	Export the universe and the list of values (LOV) files to the BusinessObjects server	21
4.14.5	Changing universes to local time format settings	21
4.15	Restarting the GSM Loader Processes.....	22
5	Rollback Procedure	24
5.1	Stopping the GSM Loaders	24
5.2	Rolling back the GSM GOM and GSM Loader Provisioning Packages to Version 1.4.2.....	24
5.3	Deploying the Version 1.4.2 Loaders	25
5.4	Restoring the GSM Version 1.4.2 Loader Configuration	26
5.5	Restoring the GSM RAN PM 1.4.2 Schema	27
5.6	Restoring the GSM SS7 1.4.2 Schema.....	27
5.7	Deploying GSM version 1.4.2 BO™ Universes	27
5.7.1	Prerequisite.....	27
5.7.2	Extracting BusinessObjects deliverables	28
5.7.3	Associating LOV files with universe	28
5.7.4	Export the universe and the list of values (LOV) files to the BusinessObjects server	28
5.7.5	Changing universes to local time format settings	29
5.8	Uninstalling GSM GOM Version 1.4.3.....	30
5.9	Uninstalling GSM RAN PM Version 1.4.3.....	30

5.10	Uninstalling GSM MSC PM Version 1.4.3	31
5.11	Uninstalling GSM E2E AT Version 1.4.3	31
5.12	Uninstalling GSM SS7 Version 1.4.3	32
5.13	Restarting the GSM Loader Processes.....	32
Notices	33

1 About this Documentation

The IBM® Tivoli® Netcool® Service Quality Manager GSM Service Solution Version 1.4.2 to 1.4.3 Upgrade Guide is organized into the following chapters:

Table 1: Document Structure

Chapter	Description
About this Documentation	An overview of the Tivoli Netcool Service Quality Manager for GSM Service Solution Upgrade Guide documentation, which gives details of the intended audience and the structure of the guide.
Software Requirements	Details of software required for the release.
Hardware Specification	Details of hardware required for the release.
Media Content	Details of media provided for the release.
Upgrade Procedure	Describes the upgrade procedure itself.
Rollback Procedure	Describes the rollback procedure from version 1.4.2 back to version 1.4.3.

1.1 Audience

The target audience of this guide is IBM Tivoli Netcool Service Quality Manager GSM Service Solution customers. They should be familiar with telecommunication and IT principles and should also have a good understanding of Solaris and/or AIX®.

IMPORTANT: Before attempting an upgrade of the Tivoli Netcool Service Quality Manager GSM Service Solution to version 1.4.3 you are strongly advised to read the release notes distributed with Tivoli Netcool Service Quality Manager GSM version 1.4.3 software. Release notes may contain information specific to your installation not contained in this guide. Failure to consult release notes may result in a corrupt, incomplete or failed installation.

Note: Tivoli Netcool Service Quality Manager Administrators should not, without prior consultation and agreement from IBM, make any changes to the database schema. Changes to the database schema may result in corruption of data and failure of the Service Quality Manager System. This applies to all releases of Tivoli Netcool Service Quality Manager using all versions of interfaces.

1.2 Required Skills and Knowledge

This guide assumes you are familiar with the following:

- General IT Principles

- Unix® Operating Systems
- IP Networking
- GSM
- Service Quality Manager modeling concepts i.e. service resources, KPIs, KQIs and SLAs

This guide also assumes that you are familiar with your company's network and with procedures for configuring, monitoring, and solving problems on your network.

1.3 Document Conventions

The following command prompts can be seen throughout this document where the user has to enter commands at the command line:

- # (hash): This prompt will be displayed if the user is logged in as user `root`.
- \$ (dollar): This prompt will be displayed if the user is logged in as either the `saserver` or `oracle` user.

Please note the above prompts are not part of commands. All commands must be entered after these prompts.

This document uses the typographical conventions shown in the following table:

Table 2: General Document Conventions

<i>Format</i>	<i>Examples</i>	<i>Description</i>
ALL UPPERCASE	GPS NULL MYWEBSERVER	Acronyms, device names, logical operators, registry keys, and some data structures.
Link	See www.sun.com	For links within a document or to the Internet.
Bold	Note: The busy hour determiner is...	Heading text for Notes, Tips, and Warnings.
SMALL CAPS	The STORED SQL dialog box... ...click VIEW... In the main GUI window, select the FILE menu, point to NEW, and then select TRAF- FIC TEMPLATE.	Any text that appears on the GUI.

<i>Italic</i>	A <i>busy hour</i> is... A web Server <i>must</i> be installed... See the <i>User Guide</i>	New terms, emphasis, and book titles.
Monospace	<code>./wminstall</code> <code>\$ cd /cdrom/cdrom0</code> <code>/xml/dict</code> <code>addmsc.sh</code> <code>core.spec</code> Type OK to continue.	Code text, command line text, paths, scripts, and file names. Text written in the body of a paragraph that the user is expected to enter.
Monospace Bold	<code>[root] # pkginfo grep -i perl</code> system Perl5 On-Line Manual Pages system Perl 5.005_03 (POD Documentation) system Perl 5.005_03	For contrast in a code example to show lines the user is expected to enter.
<Monospace italics>	<code># cd <oracle_setup></code>	Used in code examples: command-line variables that you replace with a real name or value. These are always marked with arrow brackets.
[square bracket]	<code>log-archiver.sh [-i][-w][-t]</code>	Used in code examples: indicates options.

1.4 User Publications

The following user publications are provided with the Tivoli Netcool Service Quality Manager GSM Service Solution software in Adobe® Portable Document Format (PDF).

Table 3: GSM RAN PM Service Solution Customer Documentation

Document	Description
<i>Tivoli Netcool Service Quality Manager Service Solutions Installation Guide</i>	Details the generic steps required to install any Service Quality Manager Service Solution including GSM.
<i>Tivoli Netcool Service Quality Manager GSM Interface Control Guides</i>	Details the GSM Service Solution input interfaces.
<i>Tivoli Netcool Service Quality Manager GSM Upgrade Guide</i>	Describes how to upgrade the Service Quality Manager GSM Service Solution and associated GOM from version 1.4.2 to version 1.4.3 while maintaining existing data and configuration.
<i>Tivoli Netcool Service Quality Manager GSM Service Solution Release Notes</i>	Provides information on Tivoli Netcool Service Quality Manager GSM Service Solution release contents, platform requirements, installation and upgrade procedures, and known

	issues.
--	---------

The following user publications are provided with the Tivoli Netcool Service Quality Manager Version 4.1.2 software in Adobe Portable Document Format (PDF). Online Help is available in HTML format.

Table 4: Service Quality Manager Customer Documentation and Online Help

Document	Description
<i>Release Notes</i>	Provides information on the Tivoli Netcool Service Quality Manager 4.1.2 release contents, platform requirements, installation and upgrade procedures, and known issues.
<i>Configuration Guide</i>	Describes SLA Provisioning (Parties, SLAs, and SLA Templates applications) and Service Quality Manager Provisioning (Services Resources, KQI and Service Models applications) in Service Quality Manager.
<i>Monitoring Guide</i>	Describes Monitoring (SLA Monitor, KQI Analyzer, Alarm Monitor, Audit Manager and SLA Web Monitor applications) in Tivoli Netcool Service Quality Manager.
<i>Customer Experience Manager Monitoring Guide</i>	Describes how to use and monitor the Customer Experience Management feature in Tivoli Netcool Service Quality Manager.
<i>Customer Experience Manager Provisioning Guide</i>	Reference guide containing information for provisioning the Customer Experience Manager system.
<i>Solaris Server Installation Guide</i>	Describes how to install the Tivoli Netcool Service Quality Manager Server system on Solaris 10g.
<i>Client Installation Guide</i>	Describes how to install the Tivoli Netcool Service Quality Manager Client.
<i>AIX Server Installation Guide</i>	Describes how to install the Tivoli Netcool Service Quality Manager Server system on AIX 5.3L.
<i>Solaris System Administration Guide</i>	Provides an overview of the Tivoli Netcool Service Quality Manager administrative tasks including instructions on how to complete the following tasks: <ul style="list-style-type: none"> - Starting and stopping Tivoli Netcool Service Quality Manager. - Running batch processes such as archiving trace files and log files. - Backing up and restoring the system.

<i>AIX System Administration Guide</i>	Provides an overview of the AIX Tivoli Netcool Service Quality Manager administrative tasks including instructions on how to complete the following tasks: <ul style="list-style-type: none"> - Starting and stopping Tivoli Netcool Service Quality Manager. - Running batch processes such as archiving trace files and log files. - Backing up and restoring the system.
<i>Upgrade Guide</i>	Details how to upgrade Tivoli Netcool Service Quality Manager from version 3.1.3 to version 4.1.1 (and above).
<i>Business Objects Installation & Configuration Guide</i>	Provides information on the steps required to install and configure the Business Objects (version 6.5 or Xi) Server and Client for use with Tivoli Netcool Service Quality Manager.
<i>Service Quality Manager Core Online Help</i>	Provides information and procedures for using Tivoli Netcool Service Quality Manager client applications.
<i>Customer Experience Manager Online Help</i>	Describes how to use and monitor Customer Experience Manager in Tivoli Netcool Service Quality Manager.
<i>SLA Webview Online Help</i>	Describes how to use and monitor the SLA Webview feature in the Tivoli Netcool Service Quality Manager.

2 Software Requirements

The minimum pre-requisite software requirements are:

- Tivoli Netcool Service Quality Manager Version 4.1.2 with Fix Pack 0001 (4.1.2-TIV-TNSQM-FP0001) and Interim Fix 0004 (4.1.2-TIV-TNSQM-IF0004) installed.

Note: Refer to the *Tivoli Netcool Service Quality Manager Version 4.1.2 Release Notes* for the minimum software required to operate the Service Quality Manager product.

- Tivoli Netcool Service Quality Manager GSM Service Solution version 1.4.2 is successfully installed prior to performing this upgrade.
- Any installed test data for the Tivoli Netcool Service Quality Manager GSM Service Solution is uninstalled prior to performing this upgrade.

3 Hardware Specification

Refer to the *Tivoli Netcool Service Quality Manager GSM Service Solution Release Notes* for details on the hardware specification for GSM version 1.4.2.

4 Upgrade Procedure

The upgrade procedure is composed of the following steps in sequence:

- Stopping the GSM RAN PM , MSC PM, E2E AT and SS7 loaders
- Removing GSM 1.4.2 Loader deployment files
- Backing up the GSM Loader configurations
- Installing GSM GOM (Global Object Model) version 1.4.3
- Installing GSM RAN PM version 1.4.3
- Installing GSM MSC PM version 1.4.3
- Installing GSM E2E AT version 1.4.3
- Installing GSM SS7 version 1.4.3
- Upgrading the GSM Provisioning to version 1.4.3
- Deploying the GSM version 1.4.3 loaders
- Restoring the GSM loader configurations
- Upgrading the GSM RAN PM database schema
- Upgrading the GSM SS7 database schema
- Deploying the GSM version 1.4.3 Business Objects™ Universes
- Restarting the GSM RAN PM , MSC PM, E2E AT and SS7 loaders

Refer to the sections below for details on how to complete each of the main steps identified above.

4.1 Stopping the GSM Loaders

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Gateway server only.

To stop the `GSM loader` processes, complete the following as user `saserver`:

- Execute the commands:

```
$ sap stop gsm_ran_pm_loader
$ sap stop gsm_msc_pm_loader
$ sap stop gsm_e2e_at_loader
$ sap stop gsm_ss7_loader
```

4.2 Removing GSM 1.4.2 Loader deployment files

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Gateway server only.

Complete the following as user saserver:

1. Execute the following commands:

```
$ rm $WMCROOT/conf/adapter/data/gsm_ran_pm_contextdef.xml
$ rm $WMCROOT/conf/adapter/data/gsm_ran_pm_loader_parser.bl
$ rm $WMCROOT/bin/gsm_ran_pm_loader.env
$ rm $WMCROOT/conf/adapter/data/gsm_msc_pm_contextdef.xml
$ rm $WMCROOT/conf/adapter/data/gsm_msc_pm_loader_parser.bl
$ rm $WMCROOT/bin/gsm_msc_pm_loader.env
$ rm $WMCROOT/conf/adapter/data/gsm_e2e_at_contextdef.xml
$ rm $WMCROOT/conf/adapter/data/gsm_e2e_at_loader_parser.bl
$ rm $WMCROOT/bin/gsm_e2e_at_loader.env
$ rm $WMCROOT/conf/adapter/data/gsm_ss7_contextdef.xml
$ rm $WMCROOT/conf/adapter/data/gsm_ss7_loader_parser.bl
$ rm $WMCROOT/bin/gsm_ss7_loader.env
```

4.3 Backing up the GSM Loader Configurations

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Gateway server only.

To backup the `gsm_ran_pm_loader`, `gsm_msc_pm_loader`, `gsm_e2e_at_loader` and `gsm_ss7_loader` configurations, choose a directory `<BACKUP_DIR>` where the backup will be stored, and then complete the following as user saserver:

2. Create the backup directory:

```
$ cd $WMCROOT
$ mkdir <BACKUP_DIR>
```

Where `<BACKUP_DIR>` denotes the directory where the backup is to be stored.

3. Back up the datasource configuration by executing the following commands:

```
$ cd $WMCROOT/conf/adapter/datasource
```

```
$ cp gsm_ran_pm_loader.properties
$WMCROOT/<BACKUP_DIR>/gsm_ran_pm_loader.properties.datasources

$ cp gsm_msc_pm_loader.properties
$WMCROOT/<BACKUP_DIR>/gsm_msc_pm_loader.properties.datasources

$ cp gsm_e2e_at_loader.properties
$WMCROOT/<BACKUP_DIR>/gsm_e2e_at_loader.properties.datasources

$ cp gsm_ss7_loader.properties
$WMCROOT/<BACKUP_DIR>/gsm_ss7_loader.properties.datasources
```

4. Back up the collector configuration by executing the following commands:

```
$ cd $WMCROOT/conf/adapter/collector

$ cp gsm_ran_pm_loader.properties
$WMCROOT/<BACKUP_DIR>/gsm_ran_pm_loader.properties.collector

$ cp gsm_msc_pm_loader.properties
$WMCROOT/<BACKUP_DIR>/gsm_msc_pm_loader.properties.collector

$ cp gsm_e2e_at_loader.properties
$WMCROOT/<BACKUP_DIR>/gsm_e2e_at_loader.properties.collector

$ cp gsm_ss7_loader.properties
$WMCROOT/<BACKUP_DIR>/gsm_ss7_loader.properties.collector
```

Note: Make a note of the directory location where the `gsm_ran_pm_loader`, `gsm_msc_pm_loader`, `gsm_e2e_at_loader` and `gsm_ss7_loader` configuration is backed up to, its contents may be needed at a later date if a rollback needs to be performed.

4.4 Installing GSM GOM Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Application server only.

Complete the following as user `saserver`:

1. Transfer the GSM package `ibm-tn-sqm-gsm_gom-1.4.3.tar.gz` to the `/appl` directory on the Service Quality Manager host machine.
2. Move to the `/appl` directory by executing the command:

```
$ cd /appl
```
3. Unzip the contents of the `gsm_gom` package by executing the command:

```
$ gzip -d ibm-tn-sqm-gsm_gom-1.4.3.tar.gz
```
4. Untar the contents of the `gsm_gom` package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_gom-1.4.3.tar
```

5. Verify the following files are now located in the `/appl` directory:

```
ibm-tn-sqm-gsm_gom.install
ibm-tn-sqm-gsm_gom.license
ibm-tn-sqm-gsm_gom.remove
ibm-tn-sqm-gsm_gom.sw
```

6. Execute the `gsm_gom` install procedure using the command:

```
$ ./ibm-tn-sqm-gsm_gom.install
```

Follow the on-screen prompts as directed.

4.5 Installing GSM RAN PM Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on both the Application server and Gateway server.

Complete the following as user `saserver`:

1. Transfer the GSM package `ibm-tn-sqm-gsm_ran_pm-1.4.3.tar.gz` to the `/appl` directory on the Service Quality Manager host machine.

2. Move to the `/appl` directory by executing the command:

```
$ cd /appl
```

3. Unzip the contents of the `gsm_ran_pm` package by executing the command:

```
$ gzip -d ibm-tn-sqm-gsm_ran_pm-1.4.3.tar.gz
```

4. Untar the contents of the `gsm_ran_pm` package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_ran_pm-1.4.3.tar
```

5. Verify the following files are now located in the `/appl` directory:

```
ibm-tn-sqm-gsm_ran_pm.install
ibm-tn-sqm-gsm_ran_pm.license
ibm-tn-sqm-gsm_ran_pm.remove
ibm-tn-sqm-gsm_ran_pm.sw
```

6. Execute the `gsm_ran_pm` install procedure using the command:

```
$ ./ibm-tn-sqm-gsm_ran_pm.install
```

Follow the on-screen prompts as directed.

4.6 Installing GSM MSC PM Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on both the Application server and Gateway server.

Complete the following as user `saserver`:

1. Transfer the GSM MSC PM package `ibm-tn-sqm-gsm_msc_pm-1.4.3.tar.gz` to the `/appl` directory on the Service Quality Manager host machine.

2. Move to the `/appl` directory by executing the command:

```
$ cd /appl
```

3. Unzip the contents of the `gsm_msc_pm` package by executing the command:

```
$ gzip -d ibm-tn-sqm-gsm_msc_pm-1.4.3.tar.gz
```

4. Untar the contents of the `gsm_msc_pm` package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_msc_pm-1.4.3.tar
```

5. Verify the following files are now located in the `/appl` directory:

```
ibm-tn-sqm-gsm_msc_pm.install
ibm-tn-sqm-gsm_msc_pm.license
ibm-tn-sqm-gsm_msc_pm.remove
ibm-tn-sqm-gsm_msc_pm.sw
```

6. Execute the `gsm_msc_pm` install procedure using the command:

```
$ ./ibm-tn-sqm-gsm_msc_pm.install
```

Follow the on-screen prompts as directed.

4.7 Installing GSM E2E AT Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on both the Application server and Gateway server.

Complete the following as user `saserver`:

1. Transfer the GSM MSC PM package `ibm-tn-sqm-gsm_e2e_at-1.4.3.tar.gz` to the `/appl` directory on the Service Quality Manager host machine.

2. Move to the `/appl` directory by executing the command:

```
$ cd /appl
```

3. Unzip the contents of the `gsm_msc_pm` package by executing the command:

```
$ gzip -d ibm-tn-sqm-gsm_e2e_at-1.4.3.tar.gz
```

4. Untar the contents of the `gsm_msc_pm` package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_e2e_at-1.4.3.tar
```

5. Verify the following files are now located in the `/appl` directory:

```
ibm-tn-sqm-gsm_e2e_at.install
ibm-tn-sqm-gsm_e2e_at.license
```



```
ibm-tn-sqm-gsm_e2e_at.remove  
ibm-tn-sqm-gsm_e2e_at.sw
```

6. Execute the `gsm_msc_pm` install procedure using the command:

```
$ ./ibm-tn-sqm-gsm_e2e_at.install
```

Follow the on-screen prompts as directed.

4.8 Installing GSM SS7 Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on both the Application server and Gateway server.

Complete the following as user `saserver`:

1. Transfer the GSM MSC PM package `ibm-tn-sqm-gsm_ss7-1.4.3.tar.gz` to the `/appl` directory on the Service Quality Manager host machine.
2. Move to the `/appl` directory by executing the command:

```
$ cd /appl
```

3. Unzip the contents of the `gsm_ss7` package by executing the command:

```
$ gzip -d ibm-tn-sqm-gsm_ss7-1.4.3.tar.gz
```

4. Untar the contents of the `gsm_ss7` package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_ss7-1.4.3.tar
```

5. Verify the following files are now located in the `/appl` directory:

```
ibm-tn-sqm-gsm_ss7.install  
ibm-tn-sqm-gsm_ss7.license  
ibm-tn-sqm-gsm_ss7.remove  
ibm-tn-sqm-gsm_ss7.sw
```

6. Execute the `gsm_ss7` install procedure using the command:

```
$ ./ibm-tn-sqm-gsm_ss7.install
```

Follow the on-screen prompts as directed.

4.9 Upgrading the GSM Provisioning to Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Application server only.

Complete the following as user `saserver`:

1. Execute the command:

```
$ cd $WMCROOT/packages
```

2. Upgrade the `gsm_gom` package to version 1.4.3 by executing the command:

```
$ package_upgrade -t gsm_gom_1.4.3 -s gsm_gom_1.4.2
```

Follow the on-screen prompts as directed.

3. Upgrade the `gsm_ran_pm` package to version 1.4.3 by executing the command:

```
$ package_upgrade -t gsm_ran_pm_1.4.3 -s gsm_ran_pm_1.4.2
```

Follow the on-screen prompts as directed.

4. Upgrade the `gsm_msc_pm` package to version 1.4.3 by executing the command:

```
$ package_upgrade -t gsm_msc_pm_1.4.3 -s gsm_msc_pm_1.4.2
```

Follow the on-screen prompts as directed.

5. Upgrade the `gsm_e2e_at` package to version 1.4.3 by executing the command:

```
$ package_upgrade -t gsm_e2e_at_1.4.3 -s gsm_e2e_at_1.4.2
```

Follow the on-screen prompts as directed.

6. Upgrade the `gsm_ss7` package to version 1.4.3 by executing the command:

```
$ package_upgrade -t gsm_ss7_1.4.3 -s gsm_ss7_1.4.2
```

Follow the on-screen prompts as directed.

4.10 Deploying the Version 1.4.3 Loaders

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Gateway server only.

Complete the following as user `saserver`:

1. Execute the command:

```
$ cd $WMCROOT/packages
```

2. Deploy the `gsm_ran_pm_loader` by executing the command:

```
$ wmc_ant -f adp_deploy.xml -Dsa.package=gsm_ran_pm_1.4.3 do-deploy
```

3. Deploy the `gsm_msc_pm_loader` by executing the command:

```
$ wmc_ant -f adp_deploy.xml -Dsa.package=gsm_msc_pm_1.4.3 do-deploy
```

4. Deploy the `gsm_e2e_at_loader` by executing the command:

```
$ wmc_ant -f adp_deploy.xml -Dsa.package=gsm_e2e_at_1.4.3 do-deploy
```

5. Deploy the `gsm_ss7_loader` by executing the command:

```
$ wmc_ant -f adp_deploy.xml -Dsa.package=gsm_ss7_1.4.3 do-deploy
```

4.11 Restoring the GSM Loader Configurations

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Gateway server only.

To restore the loader configurations, complete the following as user `saserver`:

1. Restore the datasource configuration by executing the commands:

```
$ cd $WMCROOT/conf/adaptor/datasource
$ cp $WMCROOT/<BACKUP_DIR>/gsm_ran_pm_loader.properties.datasource
./gsm_ran_pm_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_msc_pm_loader.properties.datasource
./gsm_msc_pm_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_e2e_at_loader.properties.datasource
./gsm_e2e_at_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_ss7_loader.properties.datasource
./gsm_ss7_loader.properties
```

2. Restore the collector configuration by executing the commands:

```
$ cd $WMCROOT/conf/adaptor/collector
$ cp $WMCROOT/<BACKUP_DIR>/gsm_ran_pm_loader.properties.collector
./gsm_ran_pm_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_msc_pm_loader.properties.collector
./gsm_msc_pm_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_e2e_at_loader.properties.collector
./gsm_e2e_at_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_ss7_loader.properties.collector
./gsm_ss7_loader.properties
```

4.12 Upgrading the GSM RAN PM Schema

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Database server only.

Complete the following as user `saserver`:

1. `cd $WMCROOT/packages/gsm_ran_pm_1.4.3/admin/oracle/schema`
2. Connect to oracle database `sadb` as user `saserver` using `sqlplus`: (**Note:** You will be prompted for the `saserver` DB user password)

```
$ sqlplus saserver@sadb
```
3. Upgrade the GSM RAN PM schema files Version 1.4.2 to Version 1.4.3 by executing the command:

```
$ @@upgd_kpi_tab.ddl;
```

4.13 Upgrading the GSM SS7 Schema

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Database server only.

Complete the following as user `saserver`:

1. `cd $WMCROOT/packages/gsm_ss7_1.4.3/admin/oracle/schema`
2. Connect to oracle database `sadb` as user `saserver` using `sqlplus`: (**Note:** You will be prompted for the `saserver` DB user password)

```
$ sqlplus saserver@sadb
```
3. Upgrade the GSM SS7 schema Version 1.4.2 to Version 1.4.3 by executing the command:

```
$ @@upgd_kpi_tab.ddl;
```

4.14 Deploying GSM version 1.4.3 BO™ Universes

Execute the instructions in the following sections to deploy the updates Universe files for these datasources:

```
ran_pm  
ss7
```

4.14.1 Prerequisite

BusinessObjects XI release 2 server with Oracle client software must be installed and configured.

Note (for distributed installations): In a distributed system, the `report.zip` file is available either on the gateway server or the application server.

Copy the `$WMCROOT/packages/gsm_<datasource name>_1.4.3/report.zip` file, as user `saserver`, from your Tivoli Netcool Service Quality Manager server to the BusinessObjects server instance using ftp or other methods available.

4.14.2 Extracting BusinessObjects deliverables

Ensure all prerequisites are met before extracting BusinessObjects deliverables. To copy the BusinessObjects deliverable to the BO server, complete the following steps:

- Create a new destination directory for the contents of the BusinessObjects deliverables.
- Transfer and unzip the `report.zip` file to the destination directory.

Depending on the contents of the BusinessObjects deliverable, some or all of the following directories can be created when the `report.zip` file is unzipped:

1. `bo_xi/logos`
2. `bo_xi/lovs`
3. `bo_xi/reports`
4. `bo_xi/universes`

4.14.3 Associating LOV files with universe

Note: List of values (LOV) files are not available for every service module. If the `bo_xi/lovs` directory does not exist, do not complete the following steps.

Before exporting the universe to the BusinessObjects repository, LOV files must be in the same folder as the universe. To comply with this requirement, complete the following steps:

1. Open the directory where the `report.zip` file was extracted to (see the *Extracting BusinessObjects deliverables* section).

Copy all contents of the `bo_xi/lovs` directory to the `bo_xi/universes` directory

4.14.4 Export the universe and the list of values (LOV) files to the BusinessObjects server

Use the BusinessObjects XI Universe Designer tool to export the universe with its LOV files. To complete the export process, complete the following steps:

1. Define a new BusinessObjects connection that points to the `sadb` database.

The `sadb` database is located in the Tivoli Netcool Service Quality Manager database server and contains the installed Tivoli Netcool Service Quality Manager Module for GSM Service module.

To complete the previous step you are required to define the following parameters within the BusinessObjects connection:

1. Database middleware: **Oracle 10**
2. Service: **Oracle service name**
3. User Name: **saserver database user**
4. Password: **Oracle password for the saserver user**

The default username and password for the `sadb` database are `saserver` and `saserver01` respectively (if the password has changed, enter the new password as appropriate). Enter the Oracle service name as previously defined in the Defining the service name using Oracle Net Manager section.

Note: To complete the connection definition, see the *Setting universe parameters → Defining a new connection* subsection in chapter 2 of the *Designer's Guide* for BusinessObjects XI release 2, available at the following link: http://help.sap.com/businessobject/product_guides/

2. Open universe file (.unv) from the `bo_xi/universes` directory.
3. Change universe connection parameters and use the new BusinessObjects connection created during step 1.
4. Save the universe with the new parameters.
5. Export the universe with its LOV files to the BusinessObjects repository.

Note: See the Exporting a universe to the repository sections in the Designer's Guide for BusinessObjects XI Release 2, at http://help.sap.com/businessobject/product_guides/.

4.14.5 Changing universes to local time format settings

Note: All universes delivered in the `report.zip` file are preset with European date formats.

If deploying on a non-European BusinessObjects system, complete the following steps:

1. Change the following objects, where applicable in the universes, to your localized time format settings:

`Week/Day/Month-Day/Hour/Sample`

These objects are normally found under the `Calendar` class.

2. Complete the following step to change from European to localized time formats. The following example details changing the objects for American date format.

To change the object format, right-click the different time objects for each time and select **object format**. Update the format with the following recommendations:

Objects Name = `Week`

ObjectFormat = `mm/dd/yyyy`

Object Name = `Day (or Month-Day)`

ObjectFormat = `mm/dd/yyyy`

Object Name = `Hour`

ObjectFormat = `mm/dd/yyyy hh:mm AM/PM`

Object Name = `Sample`

ObjectFormat = `mm/dd/yyyy hh:mm AM/PM`

Make these changes by using the BusinessObjects Universe Designer tool. For more details, see the Designer's Guide for BusinessObjects XI Release 2 available at http://help.sap.com/businessobject/product_guides/.

Access the Designer's Guide quickly using these filters:

- Select **all products** under **all products**.

Select **BusinessObjects XI Release 2** under **all releases**

4.15 Restarting the GSM Loader Processes

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Application server only.

To restart the GSM loader processes, complete the following as user `saserver`:

1. Execute the commands:

```
$ sap start gsm_ran_pm_loader
$ sap start gsm_msc_pm_loader
$ sap start gsm_e2e_at_loader
$ sap start gsm_ss7_loader
```


5 Rollback Procedure

The rollback procedure is composed of the following steps in sequence:

- Stopping the GSM loaders
- Rolling back the GSM GOM and GSM loader provisioning to version 1.4.2
- Deploying the GSM version 1.4.2 loader
- Restoring the GSM loader configuration
- Restoring the GSM RAN PM 1.4.2 schema
- Restoring the GSM SS7 1.4.2 schema
- Deploying GSM 1.4.2 BO™ Universes
- Uninstalling GSM GOM version 1.4.3
- Uninstalling GSM RAN PM version 1.4.3
- Uninstalling GSM MSC PM version 1.4.3
- Uninstalling GSM E2E AT version 1.4.3
- Uninstalling GSM SS7 version 1.4.3
- Restarting the GSM loader processes

5.1 Stopping the GSM Loaders

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Application server only.

To stop the `GSM loader` process, complete the following as user `saserver`:

- Execute the commands:

```
$ sap stop gsm_ran_pm_loader
$ sap stop gsm_msc_pm_loader
$ sap stop gsm_e2e_at_loader
$ sap stop gsm_ss7_loader
```

5.2 Rolling back the GSM GOM and GSM Loader Provisioning Packages to Version 1.4.2

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Application server only.

Complete the following as user `saserver`:

1. Execute the following command:


```
$ cd $WMCROOT/packages/gsm_gom_1.4.3/admin/provision/rollback/
```

2. Rollback the `gsm_gom` package to version 1.4.2 by executing the command:

```
$ wmc_ant -f rollback-4.1.2.xml -Dpackage.from=gsm_gom_1.4.3  
-Dpackage.name=gsm_gom_1.4.2 rollback
```

3. Execute the following command:

```
$ cd $WMCROOT/packages/gsm_ran_pm_1.4.3/admin/provision/rollback/
```

4. Rollback the `gsm_ran_pm` package to version 1.4.2 by executing the command:

```
$ wmc_ant -f rollback-4.1.2.xml -Dpackage.from=gsm_ran_pm_1.4.3  
-Dpackage.name=gsm_ran_pm_1.4.2 rollback
```

5. Execute the following command:

```
$ cd $WMCROOT/packages/gsm_msc_pm_1.4.3/admin/provision/rollback/
```

6. Rollback the `gsm_msc_pm` package to version 1.4.2 by executing the command:

```
$ wmc_ant -f rollback-4.1.2.xml -Dpackage.from=gsm_msc_pm_1.4.3  
-Dpackage.name=gsm_msc_pm_1.4.2 rollback
```

7. Execute the following command:

```
$ cd $WMCROOT/packages/gsm_e2e_at_1.4.3/admin/provision/rollback/
```

8. Rollback the `gsm_e2e_at` package to version 1.4.2 by executing the command:

```
$ wmc_ant -f rollback-4.1.2.xml -Dpackage.from=gsm_e2e_at_1.4.3  
-Dpackage.name=gsm_e2e_at_1.4.2 rollback
```

9. Execute the following command:

```
$ cd $WMCROOT/packages/gsm_ss7_1.4.3/admin/provision/rollback/
```

10. Rollback the `gsm_ss7` package to version 1.4.2 by executing the command:

```
$ wmc_ant -f rollback-4.1.2.xml -Dpackage.from=gsm_ss7_1.4.3  
-Dpackage.name=gsm_ss7_1.4.2 rollback
```

5.3 Deploying the Version 1.4.2 Loaders

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Gateway server only.

Complete the following as user `saserver`:

1. Remove the existing loader by executing the commands:

```
$ rm $WMCROOT/bin/gsm_ran_pm_loader.env  
$ rm $WMCROOT/conf/adapter/data/gsm_ran_pm_contextdef.xml  
$ rm $WMCROOT/conf/adapter/data/gsm_ran_pm_loader_parser.bl  
$ rm $WMCROOT/bin/gsm_msc_pm_loader.env
```

```
$ rm $WMCROOT/conf/adapter/data/gsm_msc_pm_contextdef.xml
$ rm $WMCROOT/conf/adapter/data/gsm_msc_pm_loader_parser.bl
$ rm $WMCROOT/bin/gsm_e2e_at_loader.env
$ rm $WMCROOT/conf/adapter/data/gsm_e2e_at_contextdef.xml
$ rm $WMCROOT/conf/adapter/data/gsm_e2e_at_loader_parser.bl
$ rm $WMCROOT/bin/gsm_ss7_loader.env
$ rm $WMCROOT/conf/adapter/data/gsm_ss7_contextdef.xml
$ rm $WMCROOT/conf/adapter/data/gsm_ss7_loader_parser.bl
```

2. Deploy the version 1.4.2 loaders by executing the commands:

```
$ cd $WMCROOT/packages
$ wmc_ant -f adp_deploy.xml -Dsa.package=gsm_ran_pm_1.4.2 do-deploy
$ wmc_ant -f adp_deploy.xml -Dsa.package=gsm_msc_pm_1.4.2 do-deploy
$ wmc_ant -f adp_deploy.xml -Dsa.package=gsm_e2e_at_1.4.2 do-deploy
$ wmc_ant -f adp_deploy.xml -Dsa.package=gsm_ss7_1.4.2 do-deploy
```

5.4 Restoring the GSM Version 1.4.2 Loader Configuration

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Gateway server only.

To restore the loader configuration, complete the following as user saserver:

1. Restore the datasource configurations by executing the commands:

```
$ cd $WMCROOT/conf/adapter/datasource
$ cp $WMCROOT/<BACKUP_DIR>/gsm_ran_pm_loader.properties.datasource
./gsm_ran_pm_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_msc_pm_loader.properties.datasource
./gsm_msc_pm_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_e2e_at_loader.properties.datasource
./gsm_e2e_at_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_ss7_loader.properties.datasource
./gsm_ss7_loader.properties
```

2. Restore the collector configuration by executing the commands:

```
$ cd $WMCROOT/conf/adapter/collector
$ cp $WMCROOT/<BACKUP_DIR>/gsm_ran_pm_loader.properties.collector
./gsm_ran_pm_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_msc_pm_loader.properties.collector
./gsm_msc_pm_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_e2e_at_loader.properties.collector
./gsm_e2e_at_loader.properties
$ cp $WMCROOT/<BACKUP_DIR>/gsm_ss7_loader.properties.collector
./gsm_ss7_loader.properties
```

5.5 Restoring the GSM RAN PM 1.4.2 Schema

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Database server only.

1. Execute the following command

```
$ cd $WMCROOT/packages/gsm_ran_pm_1.4.3/admin/oracle/schema
```

2. Connect to the Oracle database `sadb` as user `saserver` using `sqlplus`: (**Note:** You will be prompted for the `saserver` DB user password)

```
$ sqlplus saserver@sadb
```

3. Downgrade the GSM RAN PM schema from Version 1.4.3 to Version 1.4.2 by executing the command:

```
$ @@rlbk_kpi_tab.ddl;
```

5.6 Restoring the GSM SS7 1.4.2 Schema

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Database server only.

1. Execute the following command

```
$ cd $WMCROOT/packages/gsm_ss7_1.4.3/admin/oracle/schema
```

2. Connect to the Oracle database `sadb` as user `saserver` using `sqlplus`: (**Note:** You will be prompted for the `saserver` DB user password)

```
$ sqlplus saserver@sadb
```

3. Downgrade the GSM SS7 schema from Version 1.4.3 to Version 1.4.2 by executing the command:

```
$ @@rlbk_kpi_tab.ddl;
```

5.7 Deploying GSM version 1.4.2 BO™ Universes

Execute the instructions in the following sections to deploy the updates Universe files for these datasources:

`ran_pm`

`ss7`

5.7.1 Prerequisite

BusinessObjects XI release 2 server with Oracle client software must be installed and configured.

Note (for distributed installations): In a distributed system, the `report.zip` file is available either on the gateway server or the application server.

Copy the `$WMCROOT/packages/gsm_<datasource name>_1.4.2/report.zip` file, as user `saserver`, from your Tivoli Netcool Service Quality Manager server to the BusinessObjects server instance using `ftp` or other methods available.

5.7.2 Extracting BusinessObjects deliverables

Ensure all prerequisites are met before extracting BusinessObjects deliverables. To copy the BusinessObjects deliverable to the BO server, complete the following steps:

- Create a new destination directory for the contents of the BusinessObjects deliverables.
- Transfer and unzip the `report.zip` file to the destination directory.

Depending on the contents of the BusinessObjects deliverable, some or all of the following directories can be created when the `report.zip` file is unzipped:

1. `bo_xi/logos`
2. `bo_xi/lovs`
3. `bo_xi/reports`
4. `bo_xi/universes`

5.7.3 Associating LOV files with universe

Note: List of values (LOV) files are not available for every service module. If the `bo_xi/lovs` directory does not exist, do not complete the following steps.

Before exporting the universe to the BusinessObjects repository, LOV files must be in the same folder as the universe. To comply with this requirement, complete the following steps:

1. Open the directory where the `report.zip` file was extracted to (see the *Extracting BusinessObjects deliverables* section).

Copy all contents of the `bo_xi/lovs` directory to the `bo_xi/universes` directory

5.7.4 Export the universe and the list of values (LOV) files to the BusinessObjects server

Use the BusinessObjects XI Universe Designer tool to export the universe with its LOV files. To complete the export process, complete the following steps:

1. Define a new BusinessObjects connection that points to the `sadb` database.

The `sadb` database is located in the Tivoli Netcool Service Quality Manager database server and contains the installed Tivoli Netcool Service Quality Manager Module for GSM Service module.

To complete the previous step you are required to define the following parameters within the BusinessObjects connection:

1. Database middleware: **Oracle 10**
2. Service: **Oracle service name**
3. User Name: **saserver database user**
4. Password: **Oracle password for the saserver user**

The default username and password for the `sadb` database are `saserver` and `saserver01` respectively (if the password has changed, enter the new password as appropriate). Enter the Oracle service name as previously defined in the Defining the service name using Oracle Net Manager section.

Note: To complete the connection definition, see the *Setting universe parameters* → *Defining a new connection* subsection in chapter 2 of the *Designer's Guide* for BusinessObjects XI release 2, available at the following link: http://help.sap.com/businessobject/product_guides/

2. Open universe file (.unv) from the `bo_xi/universes` directory.
3. Change universe connection parameters and use the new BusinessObjects connection created during step 1.
4. Save the universe with the new parameters.
5. Export the universe with its LOV files to the BusinessObjects repository.

Note: See the Exporting a universe to the repository sections in the Designer's Guide for BusinessObjects XI Release 2, at http://help.sap.com/businessobject/product_guides/.

5.7.5 Changing universes to local time format settings

Note: All universes delivered in the `report.zip` file are preset with European date formats.

If deploying on a non-European BusinessObjects system, complete the following steps:

- 2 Change the following objects, where applicable in the universes, to your localized time format settings:

`Week/Day/Month-Day/Hour/Sample`

These objects are normally found under the `Calendar` class.

3. Complete the following step to change from European to localized time formats. The following example details changing the objects for American date format.

To change the object format, right-click the different time objects for each time and select **object format**. Update the format with the following recommendations:

Objects Name = `Week`

ObjectFormat = `mm/dd/yyyy`

Object Name = `Day (or Month-Day)`

ObjectFormat = `mm/dd/yyyy`

Object Name = `Hour`

ObjectFormat = `mm/dd/yyyy hh:mm AM/PM`

Object Name = `Sample`

ObjectFormat = `mm/dd/yyyy hh:mm AM/PM`

Make these changes by using the BusinessObjects Universe Designer tool. For more details, see the Designer's Guide for BusinessObjects XI Release 2 available at http://help.sap.com/businessobject/product_guides/.

Access the Designer's Guide quickly using these filters:

- Select **all products** under **all products**.

Select **BusinessObjects XI Release 2** under **all releases**

5.8 Uninstalling GSM GOM Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Application server only.

Complete the following as user `saserver`:

1. Change to the `/appl` directory by executing the command:

```
$ cd /appl
```

2. Execute the removal procedure using the command:

```
$ ./ibm-tn-sqm-gsm_gom.remove
```

Follow the on-screen prompts as directed.

3. Untar the contents of the GSM GOM Version 1.4.2 package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_gom-1.4.2.tar
```

4. Reinstall the GSM GOM Version 1.4.2 package to restore the GSM GOM software:

```
$ ./ibm-tn-sqm-gsm_gom.install
```

Follow the on-screen prompts as directed.

5.9 Uninstalling GSM RAN PM Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on both the Application server and Gateway servers.

Complete the following as user `saserver`:

1. Change to the `/appl` directory by executing the command:

```
$ cd /appl
```

2. Execute the removal procedure using the command:

```
$ ./ibm-tn-sqm-gsm_ran_pm.remove
```

Follow the on-screen prompts as directed.

3. Untar the contents of the GSM RAN PM Version 1.4.2 package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_ran_pm-1.4.2.tar
```

4. Reinstall the GSM RAN PM Version 1.4.2 package to restore the GSM RAN PM software:

```
$ ./ibm-tn-sqm-gsm_ran_pm.install
```

Follow the on-screen prompts as directed.

5.10 Uninstalling GSM MSC PM Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on both the Application server and Gateway servers.

Complete the following as user `saserver`:

1. Change to the `/appl` directory by executing the command:

```
$ cd /appl
```

2. Execute the removal procedure using the command:

```
$ ./ibm-tn-sqm-gsm_msc_pm.remove
```

Follow the on-screen prompts as directed.

3. Untar the contents of the GSM MSC PM Version 1.4.2 package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_msc_pm-1.4.2.tar
```

4. Reinstall the GSM MSC PM Version 1.4.2 package to restore the GSM MSC PM software:

```
$ ./ibm-tn-sqm-gsm_msc_pm.install
```

Follow the on-screen prompts as directed.

5.11 Uninstalling GSM E2E AT Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on both the Application server and Gateway servers.

Complete the following as user `saserver`:

1. Change to the `/appl` directory by executing the command:

```
$ cd /appl
```

2. Execute the removal procedure using the command:

```
$ ./ibm-tn-sqm-gsm_e2e_at.remove
```

Follow the on-screen prompts as directed.

3. Untar the contents of the GSM E2E AT Version 1.4.2 package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_e2e_at-1.4.2.tar
```

4. Reinstall the GSM E2E AT Version 1.4.2 package to restore the GSM E2E AT software:

```
$ ./ibm-tn-sqm-gsm_e2e_at.install
```

Follow the on-screen prompts as directed.

5.12 Uninstalling GSM SS7 Version 1.4.3

Note (Distributed Installation): In a distributed system, perform the procedures in this section on both the Application server and Gateway servers.

Complete the following as user `saserver`:

1. Change to the `/appl` directory by executing the command:

```
$ cd /appl
```

2. Execute the removal procedure using the command:

```
$ ./ibm-tn-sqm-gsm_ss7.remove
```

Follow the on-screen prompts as directed.

3. Untar the contents of the GSM SS7 Version 1.4.2 package by executing the command:

```
$ tar -xvf ibm-tn-sqm-gsm_ss7-1.4.2.tar
```

4. Reinstall the GSM SS7 Version 1.4.2 package to restore the GSM SS7 software:

```
$ ./ibm-tn-sqm-gsm_ss7.install
```

Follow the on-screen prompts as directed.

5.13 Restarting the GSM Loader Processes

Note (Distributed Installation): In a distributed system, perform the procedures in this section on the Application server only.

To restart the `gsm_ran_pm_loader` processes, complete the following as user `saserver`:

- Execute the commands:

```
$ sap start gsm_ran_pm_loader
```

```
$ sap start gsm_msc_pm_loader
```

```
$ sap start gsm_e2e_at_loader
```

```
$ sap start gsm_ss7_loader
```


Notices

IBM may not offer the products, services, or features discussed in this document in all countries. Consult your local IBM representative for information on the products and services currently available in your area. Any reference to an IBM product, program, or service is not intended to state or imply that only that IBM product, program, or service may be used. Any functionally equivalent product, program, or service that does not infringe any IBM intellectual property right may be used instead. However, it is the user's responsibility to evaluate and verify the operation of any non-IBM product, program, or service.

IBM may have patents or pending patent applications covering subject matter described in this document. The furnishing of this document does not grant you any license to these patents. You can send license inquiries, in writing, to:

IBM Director of Licensing
IBM Corporation
North Castle Drive
Armonk NY 10504-1785
U.S.A.

For license inquiries regarding double-byte (DBCS) information, contact the IBM Intellectual Property Department in your country or send inquiries, in writing, to:

IBM World Trade Asia Corporation
Licensing
2-31 Roppongi 3-chome
Minato-ku
Tokyo 106-0032
Japan.

The following paragraph does not apply to the United Kingdom or any other country where such provisions are inconsistent with local law: INTERNATIONAL BUSINESS MACHINES CORPORATION PROVIDES THIS PUBLICATION "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF NON-INFRINGEMENT, MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. Some states do not allow disclaimer of express or implied warranties in certain transactions, therefore, this statement may not apply to you.

This information could include technical inaccuracies or typographical errors. Changes are periodically made to the information herein; these changes will be incorporated in new editions of the publication. IBM may make improvements and/or changes in the product(s) and/or the program(s) described in this publication at any time without notice.

Any references in this information to non-IBM Web sites are provided for convenience only and do not in any manner serve as an endorsement of those Web sites. The materials at those Web sites are not part of the materials for this IBM product and use of those Web sites is at your own risk.

IBM may use or distribute any of the information you supply in any way it believes appropriate without incurring any obligation to you.

Licensees of this program who wish to have information about it for the purpose of enabling: (i) the exchange of information between independently created programs and other programs (including this one) and (ii) the mutual use of the information which has been exchanged, should contact:

IBM Corporation
5300 Cork Airport Business Park
Kinsale Road
Cork
Ireland.

Such information may be available, subject to appropriate terms and conditions, including in some cases, payment of a fee.

The licensed program described in this document and all licensed material available for it are provided by IBM under terms of the IBM Customer Agreement, IBM International Program License Agreement or any equivalent agreement between us.

Information concerning non-IBM products was obtained from the suppliers of those products, their published announcements or other publicly available sources. IBM has not tested those products and cannot confirm the accuracy of performance, compatibility or any other claims related to non-IBM products. Questions on the capabilities of non-IBM products should be addressed to the suppliers of those products.

All statements regarding IBM's future direction or intent are subject to change or withdrawal without notice, and represent goals and objectives only.

This information contains examples of data and reports used in daily business operations. To illustrate them as completely as possible, the examples include the names of individuals, companies, brands, and products. All of these names are fictitious and any similarity to the names and addresses used by an actual business enterprise is entirely coincidental.

If you are viewing this information softcopy, the photographs and color illustrations may not appear.

Trademarks

IBM, the IBM logo, and ibm.com are trademarks or registered trademarks of International Business Machines Corp., registered in many jurisdictions worldwide. Other product and service names might be trademarks of IBM or other companies. A current list of IBM trademarks is available on the Web at “Copyright and trademark information” at www.ibm.com/legal/copytrade.shtml

Adobe, the Adobe logo, PostScript, and the PostScript logo are either registered trademarks or trademarks of Adobe Systems Incorporated in the United States, and/or other countries.

UNIX is a registered trademark of The Open Group in the United States and other countries.

Other company, product or service names may be trademarks or service marks of others.

IBM®

Printed in the Republic of Ireland.