

## TESLA RMA SUBMISSION PROCESS

DA-07017-001\_v03 | March 2014

### **Application Note**

#### **DOCUMENT CHANGE HISTORY**

Version	Date	Authors	Description of Change
01	September 17, 2013	OC, DB, AI, SM	Initial Release
02	September 25, 2013	OC, SM	Updated "Common System Level Issues" section
03	March 18, 2014	OC, SM	<ul><li>Added "ECC and EDC Support on Tesla"</li><li>Updated RMA Checklist (Table 1)</li></ul>

#### **TABLE OF CONTENTS**

Introduction	1
ECC and EDC Support on Tesla	1
Tools and Diagnostics	2
nvidia-bug-report	2
nvidia-healthmon	3
NVIDIA Field Diagnostic	4
Common System Level Issues	5
RMA Checklist and Flowchart	7

## **INTRODUCTION**

NVIDIA is committed to providing the highest level of quality, reliability, and support for the enterprise datacenter-class NVIDIA<sup>®</sup> Tesla<sup>®</sup> graphics processing unit (GPU) products. To that end, NVIDIA is focused on two primary goals with the Tesla RMA submission process:

- ▶ Expeditious replacement of returned Tesla GPU products
- Comprehensive understanding of the customer-observed issue and failure to allow for:
  - NVIDIA replication and confirmation of the failure
  - Root-cause analysis of the failure aimed at continuous improvement of the product and future Tesla offerings

NVIDIA has provided this application note to ensure that the RMA requestor is able to provide the information necessary to meet these goals with each RMA request, best ensuring that such requests are quickly approved and processed.

### ECC AND EDC SUPPORT ON TESLA

NVIDIA Tesla GPU products support ECC and EDC as a protection from some common errors. All Tesla boards have ECC and EDC memory protection enabled by default. While users have an option to disable ECC, NVIDIA strongly recommends that ECC must be enabled at all times. NVIDIA will not accept RMA requests for failures that occur only with ECC disabled. Any failure must occur with ECC enabled to be eligible for RMA return.

Therefore, whenever a failure or issue is observed, always check if ECC is enabled on the Tesla board.

# **TOOLS AND DIAGNOSTICS**

NVIDIA provides a few tools to help diagnose issues and failures observed with Tesla GPU products. These tools are:

- nvidia-bug-report
- nvidia-healthmon
- NVIDIA Field Diagnostic

#### **NVIDIA-BUG-REPORT**

nvidia-bug-report.sh is a shell script included with the NVIDIA Linux driver that gathers system data that is highly valuable to understanding any reported field issue. This includes information such as lspci and system message log files and also includes nvidia-smi information. It is installed with the NVIDIA driver and placed in /usr/bin/nvidia-bug-report.sh. Running nvidia-bug-report.sh will produce an output file, nvidia-bug-report.log.tgz, in the current working directory.

Ideally, nvidia-bug-report.sh should be run immediately after an issue is observed. This will collect the most recent information about the failure.

If the report hangs or does not create a complete report, power cycle the machine, save the file that was generated, and run nvidia-bug-report.sh one more time after the power cycle to complete the log. Both logs should be sent to NVIDIA as part of any RMA submission. To run nvidia-bug-report on Linux systems, first log in to "root."

- 1. At command line # Type nvidia-bug-report.sh
- 2. Nvidia-bug-report.sh will now collect information about your system and create the file, "nvidia-bug-report.log.gz" in the current directory

Note: This file should be included with any RMA request. Failure to include this log file may result in delays to the processing of the RMA request. For more information, see the section titled, "RMA Checklist and Flowchart."

#### **NVIDIA-HEALTHMON**

nvidia-healthmon detects and troubleshoots common problems affecting Tesla GPUs in a high performance computing environment. nvidia-healthmon contains limited hardware diagnostic capabilities and instead focuses on software and system configuration issues. nvidia-healthmon is designed to discover common problems that affect a GPU's ability to run a compute job, including:

- Software configuration issues
- System configuration issues
- System assembly issues, like loose cables
- A limited number of hardware issues

To run nvidia-healthmon from the command line with default behavior on all supported GPUs:

```
user@hostname
$ nvidia-healthmon
```

nvidia-healthmon will terminate once it completes the execution diagnostics on all specified devices. An exit code of zero will be used when nvidia-healthmon runs successfully. A non-zero exit code indicates that there was a problem with the nvidiahealthmon run. The output of the application must be read to determine the exact problem. nvidia-healthmon's output may include a troubleshooting report designed to address common problems, and will often suggest a number of possible solutions. These troubleshooting steps should be undertaken from the top down, as the most likely solution is listed at the top.

For more details, command lines arguments, configuration options, and instructions for interpreting the results of the tool, refer to the *nvidia-healthmon User Guide*.

## NVIDIA FIELD DIAGNOSTIC

The NVIDIA Field Diagnostic is a comprehensive Linux based hardware diagnostic tool that provides confirmation of the numerical processing Linux engines in the GPU, integrity of data transfers to and from the GPU, and test coverage of the full onboard memory address space that is available to NVIDIA® CUDA® programs. In the event that any software or system configuration issue cannot be identified (for example, by nvidia-healthmon) and resolved, the NVIDIA Field Diagnostic should be run to determine whether the Tesla GPU may be faulty.

▶ The NVIDIA Field Diagnostic can be run with the command "./fieldiag"

Note: NVIDIA Tesla GPU products have ECC memory protection enabled by default. The NVIDIA Field Diagnostic runs only on boards that have ECC enabled. If the user has previously disabled ECC on a suspect board, ECC must be re-enabled prior to running the NVIDIA Field Diagnostic on that board. NVIDIA will not accept RMA requests for failures that occur only with ECC disabled. Any failure must occur with ECC enabled to be eligible for RMA return.

For more details or product-specific command lines arguments, refer to the *NVIDIA Field Diagnostic Quick Start Guide* (DU-05711-001) and the *NVIDIA Field Diagnostic Software Guide* (DU-05363-001) included in the NVIDIA Field Diagnostic software package.

Upon completion of the diagnostic, a fieldiag.log file is generated.

Note: This file should be included with any RMA request. Failure to include this log file may result in delays to the processing of the RMA request. For more information, see the section titled, "RMA Checklist and Flowchart."

A passing result with the NVIDIA Field Diagnostics is an indication that the NVIDIA Tesla GPU hardware is in good condition, and pointing to a potential software application-level issue.

Note: In the event that the NVIDIA Field Diagnostic returns a passing result, NVIDIA requests that data be provided illustrating that the failure follows the particular NVIDIA Tesla GPU board and details of the observed failures. Having this data will better allow NVIDIA to reproduce the issue and resolve any potential test weakness in the existing diagnostics.

## COMMON SYSTEM LEVEL ISSUES

Depending on the type and severity of the observed issue, there may be situations where it may not be possible to run nvidia-bug-report, nvidia-healthmon, or the field diagnostic. In order to better ensure that the failure is attributable to the Tesla GPU, rather than a system-level issue, and avoid any potential delays to the processing of the RMA request as a result, NVIDIA recommends that the following steps be taken to further isolate the cause of the failure.

- In addition to the power provided by the PCIe slot connector, Tesla GPU boards also require additional power from the host system. Ensure that the appropriate PCIe 8pin and/or 6-pin auxiliary power cables are properly connected to the board. Consult the product specifications for the specific Tesla GPU in use to determine the auxiliary power requirements for that particular product.
- 2. Physically remove the Tesla GPU board from the system and reinstall it to ensure that it is fully seated in the PCIe slot.
- 3. If available, replace the suspect Tesla GPU with a known good board to confirm that the observed issue or failure does not occur with the replacement.
- 4. If possible, install the suspect Tesla GPU in a different system to determine whether the observed issue or failure follows the board (or system).
  - Note: The RMA submission process will request information demonstrating that common system-level causes have been eliminated. Submitting the RMA with the information as described in Step 1 through Step 4, indicating that system level issues were eliminated will help to accelerate the RMA approval process.

Inspect your board for any obvious physical damage that may have occurred as a result of handling or installation. Figure 1 shows an example of typical physical damage found on returned boards. Note any physical damage found in the RMA request.



Figure 1. Missing or Damaged PCIe Interface Components (Capacitors)

# RMA CHECKLIST AND FLOWCHART

#### Table 1. RMA Checklist

Check Off	Item	
	<pre>nvidia-bug-report log file (nvidia-bug-report.log.gz)</pre>	
	NVIDIA Field Diagnostic log file (fieldiag.log)	
	In the event the NVIDIA Field Diagnostic returns a passing result or that the observed failure is such that the NVIDIA tools and diagnostics cannot be run, the following information should be included with the RMA request:	
	•Steps taken to eliminate common system-level causes	
	-Check PCIe auxiliary power connections	
	-Verify board seating in PCIe slot	
	-Determine whether the failure follows the board or the system	
	•Details of the observed failure:	
	-The application running at the time of failure	
	-Description of how the product failed	
	-Step-by-step instructions to reproduce the issue	
	-Frequency of the failure	
	Check if ECC is enabled at the time the failure/issue is observed	
	Is there any known or obvious physical damage to the board?	
	Submit the RMA request at <u>http://portal.nvidia.com</u>	

Note: NVIDIA Tesla GPU products have ECC memory protection enabled by default. NVIDIA will not accept RMA requests for failures that occur only with ECC disabled. Any failure must occur with ECC enabled to be eligible for RMA return.



#### Notice

The information provided in this specification is believed to be accurate and reliable as of the date provided. However, NVIDIA Corporation ("NVIDIA") does not give any representations or warranties, expressed or implied, as to the accuracy or completeness of such information. NVIDIA shall have no liability for the consequences or use of such information or for any infringement of patents or other rights of third parties that may result from its use. This publication supersedes and replaces all other specifications for the product that may have been previously supplied.

NVIDIA reserves the right to make corrections, modifications, enhancements, improvements, and other changes to this specification, at any time and/or to discontinue any product or service without notice. Customer should obtain the latest relevant specification before placing orders and should verify that such information is current and complete.

NVIDIA products are sold subject to the NVIDIA standard terms and conditions of sale supplied at the time of order acknowledgement, unless otherwise agreed in an individual sales agreement signed by authorized representatives of NVIDIA and customer. NVIDIA hereby expressly objects to applying any customer general terms and conditions with regard to the purchase of the NVIDIA product referenced in this specification.

NVIDIA products are not designed, authorized or warranted to be suitable for use in medical, military, aircraft, space or life support equipment, nor in applications where failure or malfunction of the NVIDIA product can reasonably be expected to result in personal injury, death or property or environmental damage. NVIDIA accepts no liability for inclusion and/or use of NVIDIA products in such equipment or applications and therefore such inclusion and/or use is at customer's own risk.

NVIDIA makes no representation or warranty that products based on these specifications will be suitable for any specified use without further testing or modification. Testing of all parameters of each product is not necessarily performed by NVIDIA. It is customer's sole responsibility to ensure the product is suitable and fit for the application planned by customer and to do the necessary testing for the application in order to avoid a default of the application or the product. Weaknesses in customer's product designs may affect the quality and reliability of the NVIDIA product and may result in additional or different conditions and/or requirements beyond those contained in this specification. NVIDIA does not accept any liability related to any default, damage, costs or problem which may be based on or attributable to: (i) the use of the NVIDIA product in any manner that is contrary to this specification, or (ii) customer product designs.

No license, either expressed or implied, is granted under any NVIDIA patent right, copyright, or other NVIDIA intellectual property right under this specification. Information published by NVIDIA regarding third-party products or services does not constitute a license from NVIDIA to use such products or services or a warranty or endorsement thereof. Use of such information may require a license from a third party under the patents or other intellectual property rights of the third party, or a license from NVIDIA under the patents or other intellectual property rights of NVIDIA. Reproduction of information in this specification is permissible only if reproduction is approved by NVIDIA in writing, is reproduced without alteration, and is accompanied by all associated conditions, limitations, and notices.

ALL NVIDIA DESIGN SPECIFICATIONS, REFERENCE BOARDS, FILES, DRAWINGS, DIAGNOSTICS, LISTS, AND OTHER DOCUMENTS (TOGETHER AND SEPARATELY, "MATERIALS") ARE BEING PROVIDED "AS IS." NVIDIA MAKES NO WARRANTIES, EXPRESSED, IMPLIED, STATUTORY, OR OTHERWISE WITH RESPECT TO THE MATERIALS, AND EXPRESSLY DISCLAIMS ALL IMPLIED WARRANTIES OF NONINFRINGEMENT, MERCHANTABILITY, AND FITNESS FOR A PARTICULAR PURPOSE. Notwithstanding any damages that customer might incur for any reason whatsoever, NVIDIA's aggregate and cumulative liability towards customer for the products described herein shall be limited in accordance with the NVIDIA terms and conditions of sale for the product.

#### Trademarks

NVIDIA, the NVIDIA logo, CUDA, and Tesla are trademarks and/or registered trademarks of NVIDIA Corporation in the U.S. and other countries. Other company and product names may be trademarks of the respective companies with which they are associated.

Copyright

© 2013, 2014 NVIDIA Corporation. All rights reserved.

